

VRX-58LC VIDEO RECEIVER

5.8 GHz

This is a very small 5.8 GHz wideband Video receiver for 5,65 MHz- 6,00 GHz. Fully synthesized this receiver has an SMA connector for different type of antennas for 5.8 GHz. This receiver works with any TV system and it is fully tunable.



B Features:

- ◆ 5.8 GHz Wideband
- ◆ Fully tunable
- ◆ SMA antenna connector
- ◆ 5 V battery operated
- ◆ 1 V video output
- ◆ Excellent picture quality
- ◆ High sensitivity

Technical Specifications	VRX-24S
Video Inverse Function	Yes
Polarity Protected	Yes
Battery power:	5 V
Sensitivity:	-86 dBm
Antenna Connector:	SMA
Current Consumption:	395 mA
Audio output	300 mV
Video Output	1V
Temperature Range:	-20 +70 °C
Dimensions:	3" X 3 " X 1"
Demodulation	WFM
Number of Channels	Full range tunable



www.rf-video.com

Yonge st, Toronto, ON, M4S 1Z9

Email to: info@rf-video.com

Copyright. © 2000-2007