

# LX-1700 AUDIO/VIDEO TRANSMITTER

# 1.7 GHz

LX-1700 audio/video transmitter for 1.7 GHz has great stability and broadcast picture quality. It is excellent for covert applications or experiments. This video transmitter has built-in preemphasis filter for the best color quality and it will work with any cameras- CMOS or CCD. This transmitter has 8 channels. RF output power is 1 W.



## **FEATURES:**

- 1 W RF Power
- 1700 MHz band
- SMA antenna connector
- 12 V battery operated
- RCA audio/video input
- Excellent picture quality
- Long range
- Recommended receiver VRX-1700

Technical Specifications	LX-1700
Operating Frequencies:	1700 MHz- 1800 MHz
RF Power	1 W
Channel:	1-8
DC Voltage:	12 V
Minimum required voltage:	10 V
Video distortion:	2%
Maximum range:	3-5 km
Video Format:	PAL, NTSC
Current Consumption:	1.2 A /12 V
Antenna:	N/A
Antenna Connector:	SMA
Impedance:	50 ohms
Video Connector:	RCA F
Video Impedance:	75 ohms
Video level:	1 V
Temperature Range:	-40 +75° C
Dimensions:	6.5" X 4.0 " X 2.0"
Weight:	250 grams
Modulation:	WFM



[www.rf-video.com](http://www.rf-video.com),  
2028 Yonge st, Toronto, Ont M4S 1Z9  
Email to: [info@rf-video.com](mailto:info@rf-video.com).  
Copyright. © 2002-2005