



MX-50/65T MEDIUM POWER VIDEO SENDER

RF-links.com introduces a small low cost Video sender for TV production and Film. Model **MX-50/65** has **1 mW RF** power and it is excellent low cost solution for Steadicam operators. The range is 30-100 ft, maximum 300 ft in the open area. Channels are tunable from 65-69 UHF air band.
NOTE: DO NOT EXCEED VOLTAGE OVER 14.4 V!



Technical Specifications	
SIZE:	2.4" X 1.5" X 0.7"
RF POWER	1 mW
CURRENT CONSUMPTION	28 mA/ 9 V
ANTENNA CONNECTOR	BNC
UHF CHANNELS	65-69
POWER SUPPLY	9 V - 12 V
VIDEO INPUT	1V/ 75 OHM
RANGE	app. 100 ft
POLARITY PROTECTED	YES