

RM-900 AUDIO/VIDEO RECEIVER

900 MHz

The newest AM receiver for 900 MHz Model RM-900 is a high sensitive receiver for AM band 900 MHz. It is extremely stable, with fully tunable function and excellent color picture and sound. This receiver needs 12 V / 200 mA. Antenna connector is a BNC type and it is possible to use different kind of antennas with gain. RM-900 is excellent match for any of our AM video transmitters: SPX 916, XLT 900, HPX 916 or any other AM (Amplitude modulated) video transmitter in 900- 958 MHz range...



FEATURES:

- 900 MHz- 958 MHz
- BNC antenna connector
- 12 V battery operated
- RCA audio/video out
- Excellent picture quality
- Very sensitive
- Frequency tunable

Technical Specifications	RM-900
Operating Frequencies:	900 MHz- 958 MHz
Channel:	Frequency tunable
DC Voltage:	12 V
Minimum required voltage:	10 V
Battery power:	12 V – 14 V
Video distortion:	2%
Maximum range:	N/A
Video Format:	PAL, NTSC
Current Consumption:	0.3 A / 12 V
Antenna:	N/A
Antenna Connector:	BNC
Impedance:	50 ohms
Video Connector:	RCA F
Video Impedance:	75 ohms
Video level:	1 V
Temperature Range:	-40 +75* C
Dimensions:	5" X 4 " X 1.2"
Weight:	250 grams
Modulation:	Negative AM



www.rf-video.com,
2028 Yonge st, Toronto, Ont M4S 1Z9
Email to: info@rf-video.com.
Copyright. © 2002-2005