



VRX-58DY

Audio/Video Diversity Receiver

5.8 GHz

This small receiver is definitely the best diversity 5.8 GHz Video receiver on the market. This receiver is fully synthesized and it has built-in 2 SMA antenna connectors for 5.8 GHz. This receiver has 8 channels in 5.8 GHz band.



Technical Specifications	
Operating Frequencies:	5650-5900 MHz
Channel:	Channels from 1-8
DC Voltage:	9 V – 12 V
Sensitivity:	-86 dBm
Type:	Antenna diversity
Minimum required voltage:	10 V
Battery power:	12 V
Video distortion:	3%
Maximum range:	N/A
Video Format:	PAL, NTSC
Current Consumption:	350 mA / 12 V
Antenna:	N/A
Antenna Connectors:	SMA x2
Impedance:	50 ohms
Audio outputs:	300 mV
Video/Audio Connectors:	RCA F
Video Impedance:	75 ohms
Video level:	1 V
Temperature Range:	-10 +65 °C
Dimensions:	4.3" X 2.8 " X 1.0"
Weight:	100 grams
Demodulation:	WFM