

VRX-58L VIDEO RECEIVER

This is the most sensitive and definitely the best 5.8 GHz Video receiver on the market. Fully synthesized this receiver has an SMA connector for different type of antennas for 5.8 GHz. This receiver works with any TV system and it has 8 selectable channels.



Features:

- ◆ 5.8 GHz Wideband
- ◆ Select Channels
- ◆ SMA antenna connector
- ◆ 12V battery operated
- ◆ 1V video output
- ◆ Excellent picture quality
- ◆ High sensitivity
- ◆ Fully tunable in 5.6 – 5.9 GHz

Technical Specifications	VRX-24S
Video Inverse Function	Yes
Polarity Protected	Yes
Minimum required voltage:	10 V
Battery power:	9V- 12 V
Sensitivity:	-86 dBm
Antenna Connector:	SMA
Current Consumption:	350 mA
Audio output	300 mV
Video Output	1V
Temperature Range:	-20 +70 °C
Dimensions:	4.7" X 3 " X 1.0"
Demodulation	WFM
Number of Channels	8 Channels in 5.7 GHz – 5.8 GHz Band



www.rf-video.com

Yonge st, Toronto, ON, M4S 1Z9

Email to: info@rf-video.com

Copyright. © 2000-2007