

# VRX-1700 AUDIO/VIDEO RECEIVER

# 1.7 GHz

The new receiver model VRX-1700 is fully synthesized unit with 8 easy to change channels. Antenna connector is an SMA. VRX-1700 has 8 selectable channels.



## **FEATURES:**

- 1700 MHz
- SMA antenna connector
- 12 V battery operated
- RCA video output
- Two audio outputs
- Excellent picture quality
- High sensitivity

Technical Specifications	VRX-1700
Operating Frequencies:	1700 MHz- 1800 MHz
Channel:	1-8
DC Voltage:	12 V
Minimum required voltage:	10 V
Video distortion:	3%
Sensitivity:	-89 dBm
Video Format:	PAL, NTSC
Current Consumption:	300 mA / 12 V
Antenna:	N/A
Antenna Connector:	SMA
Impedance:	50 ohms
Video Connector:	RCA F
Video Impedance:	75 ohms
Video level:	1 V
Temperature Range:	-40 +75* C
Dimensions:	5.7" X 2.5" X 0.8"
Weight:	220 grams
Modulation:	WFM



[www.rf-video.com](http://www.rf-video.com),

Email to: [info@rf-video.com](mailto:info@rf-video.com).

Copyright. © 2002-2012