
VRX-54SH

Audio/Video Receiver

5.4 GHz

This small receiver is definitely the best 5.4 GHz Video receiver on the market. Fully synthesized this receiver has an SMA connector for different type of antennas for 5.4 GHz. This receiver has 8 channels in 5.4 GHz band.



Technical Specifications	
Operating Frequencies:	5400 MHz
Channel:	Channels from 1-8 changing by push button
DC Voltage:	9 V – 12 V
Sensitivity:	-86 dBm
Minimum required voltage:	10 V
Battery power:	12 V
Video distortion:	3%
Maximum range:	N/A
Video Format:	PAL, NTSC
Current Consumption:	350 mA / 12 V
Antenna:	N/A
Antenna Connector:	SMA
Impedance:	50 ohms
Audio outputs:	300 mV
Video/Audio Connectors:	RCA F
Video Impedance:	75 ohms
Video level:	1 V
Temperature Range:	-10 +65 °C
Dimensions:	1.5" X 2.8 " X 0.75"
Weight:	80 grams
Demodulation:	WFM