

# VRX-58 VIDEO RECEIVER

# 5.8 GHz

This small receiver is definitely the best 5.8 GHz Video receiver on the market. Fully synthesized this receiver has an SMA connector for different type of antennas for 5.8 GHz. This receiver is tunable and it covers all frequencies in 5.8 GHz band. This receiver can access any video TV transmitter in 5.8 GHz band.



## Features:

- ◆ 5.8 GHz Wideband
- ◆ Select Channels
- ◆ SMA antenna connector
- ◆ 12V battery operated
- ◆ 1V video output
- ◆ Excellent picture quality
- ◆ High sensitivity
- ◆ Fully tunable in 5.6 – 5.9 GHz

Technical Specifications	VRX-24S
Operating Frequencies:	5700 MHz- 5900 Mhz
Channel:	Tunable from 5.7 GHz-5.9 GHz
DC Voltage:	9 V- 12 V
RF power:	N/A
Minimum required voltage:	10 V
Audio Carriers:	6 MHz, 6.5MHz
Battery power:	12 V
Video distortion:	3%
Sensitivity:	-86 dBm
Video Format:	PAL, NTSC
Current Consumption:	350 mA / 12 V
Antenna:	Recommended high gain
Antenna Connector:	SMA
Impedance:	50 ohms
Video/Audio Connector:	RCA F
Video Impedance:	75 ohms
Audio input	300 mV
Carrier frequencies for audio channels:	N/A
Temperature Range:	-40 +78 °C
Dimensions:	4.3" X 2.8 " X 1.0"
Weight:	100 grams
Demodulation	WFM



[www.rf-video.com](http://www.rf-video.com)

Email to: [info@rf-video.com](mailto:info@rf-video.com)

Copyright. © 2000-2012