

VRX-58S VIDEO RECEIVER

5.8 GHz

This small receiver is definitely the best 5.8 GHz Video receiver on the market. Fully synthesized this receiver has an SMA connector for different type of antennas for 5.8 GHz. This receiver has 8 preprogrammed channels in 5.8 GHz band.



Features:

- ◆ 5.8 GHz Wideband
- ◆ Select Channels
- ◆ SMA antenna connector
- ◆ 12V battery operated
- ◆ 1V video output
- ◆ Excellent picture quality
- ◆ High sensitivity
- ◆ Fully tunable in 5.6 – 5.9 GHz

Technical Specifications	VRX-24S
Operating Frequencies:	5650 MHz- 5900 Mhz
Channel:	Tunable from 1-8
DC Voltage:	9 V- 12 V
RF power:	N/A
Minimum required voltage:	10 V
Audio Carriers:	6 MHz, 6.5MHz
Battery power:	12 V
Video distortion:	3%
Sensitivity:	-86 dBm
Video Format:	PAL, NTSC
Current Consumption:	350 mA / 12 V
Antenna:	N/A
Antenna Connector:	SMA
Impedance:	50 ohms
Video/Audio Connector:	RCA F
Video Impedance:	75 ohms
Audio output	300 mV
Video level	1V
Temperature Range:	-10 +65 °C
Dimensions:	4.3" X 2.8 " X 1.0"
Weight:	100 grams
Demodulation	WFM



www.rf-video.com

Yonge st, Toronto, ON, M4S 1Z9

Email to: info@rf-video.com

Copyright. © 2000-2007