

VRX-2000 VIDEO RECEIVER WITH DISPLAY 900-2000 MHz

VRX-2000 is an excellent PLL controlled Audio/video receiver easy to use. This is a wideband receiver that works from 900 MHz- 2000 MHz. It is a very stable and sensitive video receiver for a very wide range of frequencies.



FEATURES:

- 900 MHz - 2100 MHz
- BNC antenna connector
- 12 V battery operated
- RCA audio/video outputs
- Excellent picture quality
- Extremely sensitive
- Built-in Low-noise amplifier

Technical Specifications	VRX-2000
Operating Frequencies:	900 MHz- 2100 MHz
Channel:	N/A
DC Voltage:	12 V
RF power:	N/A
Minimum required voltage:	10 V
Battery power:	12 V
Sensitivity:	-100 dBm
Maximum range:	N/A
Video Format:	PAL, NTSC
Current Consumption:	0.6 A / 12 V
Antenna:	N/A
Antenna Connector:	BNC
Impedance:	50 ohms
Channel settings:	PLL controlled external
Video Connector:	RCA F
Video Impedance:	75 ohms
Video level:	1 V
Temperature Range:	-25 +75* C
Dimensions:	N/A
Weight:	150 grams
Demodulation:	WFM analog



www.rf-video.com,
2028 Yonge st, Toronto, Ont M4S 1Z9
Email to: info@rf-video.com.
Copyright. © 2002-2005