

## FCN-900 VIDEO RECEIVER

The newest FM receiver for 900 MHz - 1400 MHz Model FCN- 900 is definitely the smallest FM receiver in the world of its kind. It is extremely stable, with fully tunable function and amazing color picture. This receiver works on 12 V / 280 mA. Antenna connector is a TV F type and it is possible to use different kind of antennas with gain. It is definitely smallest receiver on the market for this band!

### FEATURES:



- 900 MHz-1400 MHz
- Built-in antenna
- 12 V battery operated
- RCA video output
- Excellent picture quality
- Very sensitive
- Tunable frequencies

Technical Specifications	FCN-900
Operating Frequencies:	900 MHz- 1400 MHz
Channel:	Tunable channels
DC Voltage:	12 V
Minimum required voltage:	10 V
Battery power:	12 V - 14 V
Video distortion:	2%
Maximum range:	N/A
Video Format:	PAL, NTSC
Current Consumption:	280 mA / 12 V
Antenna:	N/A
Antenna Connector:	F; BNC on request
Impedance:	50 ohms
Video Connector:	RCA F
Video Impedance:	75 ohms
Video level:	1 V
Temperature Range:	-40 +75* C
Dimensions:	6.5" X 4.0 " X 2.0"
Weight:	70 grams
Demodulation:	WFM



[www.rf-video.com](http://www.rf-video.com),

Email to: [info@rf-video.com](mailto:info@rf-video.com).

Copyright. © 2002-2012