

RCN-900 AUDIO/VIDEO RECEIVER

900 MHz

The newest AM receiver for 900 MHz Model RCN 900 is definitely the smallest and the best receiver in the world of it's kind. It is extremely stable, with fully tunable function and amazing color picture. This receiver needs 12 V / 180 mA. Antenna connector is a BNC type and it is possible to use different kind of antennas with gain. Model RCN 900/A has built-in audio function. The size of the receiver is unbelievable- this unit measures 3" X 2.5" X 0.8" and it is definitely smallest receiver on the market! RCN-900 is combined with any of our AM video transmitters: SPX 916, XLT 900, HPX 916... FCC COMPLIANT.



FEATURES:

- 900 MHz- 935 MHz
- BNC antenna connector
- 12 V battery operated
- RCA audio/video out's
- Excellent picture quality
- Very sensitive
- Fully tunable

Technical Specifications	RCN-900
Operating Frequencies:	900 MHz- 935 MHz
Channels:	Tunable function
DC Voltage:	12 V
Minimum required voltage:	10 V
Battery power:	12 V- 14 V
Video distortion:	2%
Maximum range:	N/A
Video Format:	PAL, NTSC
Current Consumption:	0.2 A / 12 V
Antenna:	N/A
Antenna Connector:	BNC
Impedance:	50 ohms
Video Connector:	RCA F
Video Impedance:	75 ohms
Video level:	1 V
Temperature Range:	-40 +75° C
Dimensions:	3" X 2 " X 0.8"
Weight:	80 grams
Demodulation:	Negative AM



www.rf-video.com,

Email to: info@rf-video.com.

Copyright. © 2002-2012