

ZH-1714 POWER AMPLIFIER

5.8 GHz

This is the special version of high power microwave amplifier for 5.7 GHz made for Military applications. It requires only 80 mW RF power for a full 5 W power in 1.7 GHz band. Power supply is 12 V / 1.8 A. Weight 680 grams.



Features:

- ◆ 5.8 GHz Wideband
- ◆ Low noise figure
- ◆ SMA or BNC Antenna connector
- ◆ Built-in microwave filter
- ◆ Excellent picture quality
- ◆ 1 Year Warranty

Technical Specifications	VRX-24S
Thermal Protected	Yes
Battery power:	12- 14 V
Operating Frequency	5600-5890 MHz
Antenna Connector:	SMA or BNC
Current Consumption:	1.8 A/12.6 V
RF input/output	50 ohms
Temperature Range:	-20 +70 °C
Dimensions:	5" X 2.2 " X 0.8"



www.rf-video.com

Yonge st, Toronto, ON, M4S 1Z9

Email to: info@rf-video.com

Copyright. © 2000-2007